

# AIR COMPRESSORS 120-Gallon




STATIONARY - ELECTRIC - TWO STAGE


*This 120 gallon air compressor is designed for the most demanding applications where dependable air supply is essential. This high-capacity air compressor offers maximum air delivery day-in and day-out.*



AM2-HE20-120M



Quality two stage compressor



Dual large canister intake filters



Industrial electric motor for a long life

**Compressor Pump:** Splash lubricated cast iron crankcase · Cast iron head · Cast iron cylinder · Two-stage intercooler · Oil sight glass

**Motor:** Auto start/stop · Magnetic starter with mounting box and wiring

**Frame:** Powder coated ASME coded 120-gallon receiver tank · 7-gauge base plate to reduce vibration · 14-gauge one-piece expanded metal belt guard for improved cooling

**Components:** Industrial grade pressure switch · Large fly wheel for extra cooling and longer life · Manual drain valves for proper maintenance

Model No.	CFM @ 175 PSI	Horsepower	Pump	Dimensions (LxWxH)	Ship Wt.	Net Wt.
AM2-HE10-120M	30.5	10.0 HP Electric	Cast iron	74in.x28in.x50in.	904 lbs.	785 lbs.
AM2-HE15-120M	43.8	15.0 HP Electric	Cast iron	74in.x28in.x55in.	995 lbs.	876 lbs.
AM2-HE20-120M*	54.9	20.0 HP Electric	Cast iron	74in.x28in.x58in.	1100 lbs.	981 lbs.

\*Model will be available in March 2009.

### Options

AX-0048	230V, Single-phase, 39.0A - Configures unit for 230V single-phase power
AX-0049	200V, Three-phase, 30.8A - Configures unit for 200V three-phase power
AX-0050	230V, Three-phase, 26.8A - Configures unit for 230V three-phase power
AX-0051	460V, Three-phase, 13.4A - Configures unit for 460V three-phase power
AX-0052	200V, Three-phase, 44.0A - Configures unit for 200V three-phase power
AX-0053	230V, Three-phase, 38.0A - Configures unit for 230V three-phase power
AX-0054	460V, Three-phase, 19.0A - Configures unit for 460V three-phase power
AX-0055	200V, Three-phase, 55.0A - Configures unit for 200V three-phase power
AX-0056	230V, Three-phase, 48.0A - Configures unit for 230V three-phase power
AX-0057	460V, Three-phase, 24.0A - Configures unit for 460V three-phase power

\*All options add starter to model.

Model #	AX-0048	AX-0049	AX-0050	AX-0051	AX-0052	AX-0053	AX-0054	AX-0055	AX-0056	AX-0057
AM2-HE10-120M	●		●	●						
AM2-HE15-120M					●	●	●			
AM2-HE20-120M								●	●	●